



EN Operator's manual
smart Gateway

GARDENA smart Gateway

1. SAFETY	4
2. FUNCTION	5
3. INITIAL OPERATION	6
4. OPERATION	15
5. MAINTENANCE	16
6. STORAGE	16
7. TROUBLESHOOTING	17
8. TECHNICAL DATA	18
9. SERVICE/WARRANTY	19

Translation of the original instructions.



For safety reasons, children and young people under 16 as well as anyone who is not familiar with these operating instructions should not use the product. Persons with reduced physical or mental abilities may use the product only if they are supervised or instructed by a responsible person. Children must be supervised to ensure that they do not play with the product. Never operate the product when you are tired, ill or under the influence of alcohol, drugs or medicine.

Intended use:

The **GARDENA smart Gateway** is intended for private use in domestic and hobby gardens for automatic control of smart system products by the **GARDENA smart system App**.

The **GARDENA smart Gateway** is controlled and operated by the **GARDENA smart system App**.

1. SAFETY

Important!

Read the operator's manual carefully before use and keep for future reference.



DANGER!

Risk of suffocation!

Small parts can be easily swallowed. There is also a risk that the polybag can suffocate toddlers. Keep toddlers away when you assemble the product.



DANGER! Cardiac arrest!

This product makes an electromagnetic field while it operates. This field may under some conditions interfere with active or passive medical implants. To decrease the risk of conditions that can possibly injure or kill,

we recommend persons with medical implants to speak with their physician and the medical implant manufacturer before you operate the product.

Do not open the product.

Only use the product with the supplied Power supply unit.

Protect the power supply unit from moisture when connected.

The product can be used in the temperature range 0 °C to +40 °C.


Don't use cables – connecting the products to external/outdoor interfaces.

Short Range Device Antennas and Wi-Fi Antenna are installed in the product.

Power over Ethernet is not possible.

2. FUNCTION

LED-Display:



Internet LED:

Green:

Yellow:

Red:

Red flashing:

Connected with router and server

Hotspot mode – not connected with router

Not connected

Connected with router; not connected with server



Connection LED:

Green flashing:

Yellow flashing:

Receiving data

Sending data



Power LED:

Green:

Green flashing:

Yellow:

Yellow flashing:

Red:

Power On

Booting

1. Factory reset running

2. Error (restart required)

Software update

Fatal error (restart required)


3. INITIAL OPERATION

Contents:

- smart Gateway
- Power supply unit
- Ethernet-cable

To update the firmware of the smart Gateway:

An Internet connection is required for installation of the Gateway. To be able to use all functions of the Gateway we recommend to update the firmware.



1. Connect the power supply unit to a mains socket.
2. Connect the power supply cable to the plug socket ④ of the Gateway.
3. Connect the Gateway with the provided network cable to your router.
*The software for your Gateway is now being updated. This process can take up to 15 minutes (depending on your Internet connection).
Once the Internet-LED and the Power LED permanently illuminate green, the Gateway is up to date.
The Gateway can now be included in the smart system App. You can continue to use the LAN cable for this or include it now via WLAN.*


Now you can choose the location of the Gateway.

The correct location for the Gateway:

- We recommend installing the Gateway near the garden window.
- Only use the product indoors.
- Do not use in cellar or nearby metal plates or engines.
- Radio transmission may be disturbed by external influences such as electric motors or defective electrical devices.
- The radio range may be restricted in buildings (e. g. by reinforced concrete walls) or outdoors (e. g. by high humidity).
- Avoid the influence of moisture, dust, sunlight or other heat radiation.


To mount the Gateway on the wall (optional):

The two screws (not supplied) for attaching the Gateway have to be screwed into place **A** horizontally 75 mm/**B** vertically 50 mm apart and the screw head diameter must not exceed 8 mm.



1. Screw the screws into the wall **A** 75 mm/**B** 50 mm apart.
2. Attach the Gateway.


To operate via ethernet cable (recommended):




1. Download the **GARDENA smart system App** from the Apple App Store or the Google Play Store.
2. Follow the instructions in the App.

To connect to a Wi-Fi network:

The LAN cable must be unplugged in order to activate the configuration network (yellow Internet LED illuminates). If it illuminates still red, briefly push the reset button ⑦.



The configuration network is activated as long as the Internet LED permanently illuminates yellow.



The configuration network remains active for 15 minutes. After the 15 minutes have elapsed, the configuration network can be reactivated by briefly pushing the reset button ⑦.

To configure the Wi-Fi network with an iOS device (iPhone, iPad):

1. Download the **GARDENA smart system App** from the Apple App Store.
2. Follow the instructions in the App.

Apple HomeKit code on bottom of Gateway available

1. Wait until the Internet LED lights up yellow permanently (the configuration network is activated).

If the Internet LED is red, briefly press the reset button to activate the configuration network.

Apple HomeKit code not available on bottom of Gateway

- | | |
|--|---|
| <ol style="list-style-type: none"> 1. Wait until the Internet LED lights up yellow permanently (the configuration network is activated).

If the Internet LED is red, briefly press the reset button to activate the configuration network. | <p>Open the GARDENA smart system App and follow the instructions for initial setup.</p> |
| <ol style="list-style-type: none"> 2. Open the Apple Home App (located by default on your mobile iOS device). | <p>Then go under in the GARDENA smart system App:
<i>My garden</i> → <i>Include device</i> → <i>Integrations/Apple HomeKit</i>.

The Apple HomeKit setup code will now be displayed.</p> |
| <ol style="list-style-type: none"> 3. Choose "<i>Include device</i>". | <p>Make a note of this code (Info: the code remains permanently the same and belongs firmly to your Gateway).</p> |

Apple HomeKit code on bottom of Gateway available**Apple HomeKit code not available on bottom of Gateway**

4. Scan the HomeKit label **on the bottom of the Gateway**.

Wait until the Internet LED lights up yellow permanently (the configuration network is activated).

If the Internet LED is red, briefly press the reset button to activate the configuration network.

-
5. Wait until the Internet LED and the Power LED light up permanently green.

Open the **Apple Home App** (located by default on your mobile iOS device) and follow the instructions:

- *Add device*
- *Code missing or cannot be scanned*
- *Enter manual code*


-
6. The Gateway can now be integrated into the **GARDENA smart system App**.

Wait until the Internet LED and the Power LED light up permanently green.

To configure a WLAN network using an Android device or a web app (<https://smart.gardena.com>):

Wait until the Internet LED illuminates yellow permanently (the configuration network is activated).

To establish a connection via Wi-Fi, you need your Gateway ID. The Gateway ID can be read on the sticker on the underside of the Gateway. You will also need the password for your Wi-Fi network.



1. Connect to the GARDENA configuration network. To do this, go to the Wi-Fi settings on your smartphone, tablet or computer. *The Gateway should now be displayed there as an available Wi-Fi network.*
The network name starts with “GARDENA_config.xxxx”.
2. Connect to this network.
3. Open the URL:


<http://10.0.0.1>

in your preferred Internet browser. (Also, make sure JavaScript is activated and browser cookies are accepted, in order to display the page correctly. Connecting the Gateway is not supported by Internet Explorer. Please use a different browser e.g. Safari/Google Chrome.)
You should now see the Gateway Interface.

Gateway ID: 9eb74563-e89b-12d3-a456-426655446548

Password Gateway Interface:
9eb74563

4. Login using the first eight digits of your Gateway ID as the password (see graphic). **The Gateway ID is located on the bottom side of the Gateway.**
5. Under **WLAN Network**, select your own WLAN network that you want to use to connect the Gateway to the Internet.
6. Enter your own Wi-Fi network password and confirm your settings.
7. Wait until the Internet LED and the Power-LED permanently illuminate green.
The Gateway can now be included in the GARDENA smart system App.



Note: Because the GARDENA configuration network does not have its own Internet access, your smartphone/tablet may automatically leave the GARDENA configuration network or displays an error message. In this case, you must allow a connection without Internet access to be maintained in the settings of your smartphone/tablet.


4. OPERATION

To operate with the GARDENA smart system App:

You can use the **GARDENA smart system App** to control all smart system products from anywhere at any time. You can download the free **GARDENA smart system App** from the Apple App Store or from the Google Play Store.

All GARDENA smart products are integrated via the app. Follow the instructions inside the App.


Factory Reset:



The smart Gateway will be reset to the factory settings (not deleted from an existing Gardena Smart system account).

You may need to use the reset function if for example you want to link your Gateway to a new Wi-Fi network.

1. Disconnect the Gateway from the power supply.
1. Push and hold down the Reset key ⌚; while you reconnect the Gateway to the mains, until the Power-LED lights up yellow.
2. Release the reset button ⌚ and start the initial operation (see 3. INITIAL OPERATION).
4. Wait until the power LED lights green.
This may take up to 15 minutes.



5. MAINTENANCE

To clean the Gateway:

No caustic/abrasive cleaning agents should be used.

→ **Clean Gateway with a damp cloth (do not use solvent).**

6. STORAGE

To put into storage:

The product must be stored away from children.

→ Do not stow the product outdoors if not in use.

Disposal:

(in accordance with RL2012/19/EC)



The product must not be disposed of to normal household waste. It must be disposed of in line with local environmental regulations.

IMPORTANT!

Dispose of the product through or via your municipal recycling collection centre.

7. TROUBLESHOOTING

Problem:

The internet LED flashes red.

Possible Cause:

The Gateway does not reach the required ports.

Remedy:

Outgoing connections from the Gateway must be able to reach the following ports in the Internet and/or your Router. (Usually no configuration needs to be changed, this list is a reference for advanced users.):

- 53 TCP / UDP (DNS)
- 67/68 UDP (DHCP)
- 123 TCP / UDP (NTP)
- 80 TCP (HTTP)
- 443 TCP (HTTPS)



NOTE: For any other malfunctions please contact the GARDENA service department. Repairs must only be done by GARDENA service departments or specialist dealers approved by GARDENA.

8. TECHNICAL DATA

	Unit	Value
Operation temperature range (indoors)	°C	0 to +40
Internal SRD:		
Frequency range	MHz	863 – 870
Maximum power	mW	25
Free field radio range	m (approx.)	100
Wi-Fi		
Frequency range	MHz	2400 – 2483,5
Maximum power	mW	100
Standards supported		IEEE 802.11b/g/n
Ethernet		
Port		1 LAN port via RJ45 socket
Data connection		Standard Ethernet 10/100 Base-T
Power supply unit		
Mains voltage	V (AC)	100 – 240
Mains frequency	Hz	50 – 60
Max. output voltage	V (DC)	5
Rated output current	A	1
Input ratings of the Gateway unit	V (DC) / A	5 / 1
Dimensions (W x H x D)	mm	57 x 128 x 58
Weight	g	120

EC Declaration of Conformity:

Hereby, GARDENA Manufacturing GmbH declares that the radio equipment type (Art. 19000/19005) is in compliance with directive 2014/53/EU.

The full text of the EC declaration of conformity is available at the following internet address:

<http://www.gardena.com/int/support/safety-regulations>

9. SERVICE/WARRANTY

Service:

Please contact the address on the back page.

Warranty statement:

In the event of a warranty claim, no charge is levied to you for the services provided.

GARDENA Manufacturing GmbH grants a warranty for all original GARDENA new products for two years from the date of original purchase from the retailer, provided that the devices have been for private use only. This manufacturer's warranty does not apply to products acquired second hand.

This warranty includes all significant defects of the product that can be proved to be material or manufacturing faults.

This warranty is fulfilled by supplying a fully functional replacement product or by repairing the faulty product sent to us free of charge; we reserve the right to choose between these options. This service is subject to the following provisions:

- The product has been used for its intended purpose as per the recommendations in the operating instructions.
- Neither the purchaser nor a third party has attempted to open or repair the product.
- Only Original GARDENA replacement parts and wear parts have been used for operation.
- Presentation of the receipt

Normal wear and tear of parts and components (such as blades, blade fixing parts, turbines, light bulbs, V-belts/toothed belts, impellers, air filters, spark plugs), visual changes, wear parts and consumables are excluded from the warranty.

This manufacturer's warranty is limited to replacement and repair of products in accordance with the abovementioned conditions. The manufacturer's warranty does not constitute an entitlement to lodge other claims against us as a manufacturer, such as for damages. This manufacturer's warranty does **not**, of course, affect statutory and contractual warranty claims against the dealer/retailer.

The manufacturer's warranty is governed by the law of the Federal Republic of Germany.

In case of a warranty claim, please return the faulty product, together with a copy of the receipt and a description of the fault, with postage paid to the service address.

Product liability:

In accordance with the German Product Liability Act, we hereby expressly declare that we accept no liability for damage incurred from our products where said products have not been properly repaired by a GARDENA approved service partner or where original GARDENA parts or parts authorised by GARDENA were not used.

Open Source Software:

This device contains open source software. GARDENA hereby offers to deliver, upon request, a copy of the complete corresponding source code for the copyrighted open source software packages used in this product for which such offer is requested by the respective licenses. This offer is valid up to three years after product purchase to anyone in receipt of this information. To obtain the source code, please write in English, German or French to:

smart.open.source@husqvarnagroup.com

Deutschland / Germany

GARDENA
 Manufacturing GmbH
 Central Service
 Hans-Lorenser-Straße 40
 D-89079 Ulm
 Produktfragen:
 (+49) 731 490-123
 Reparaturen:
 (+49) 731 490-290
 service@gardena.com

Albania

COBALT Sh.p.k.
 Rr. Siri Kodra
 1000 Tirana
Argentina
 Husqvarna Argentina S.A.
 Av.del Libertador 5954 –
 Piso 11 – Torre B
 (C1248ARP) Buenos Aires
 Phone: (+54) 11 5194 5000
 info.gardena@
 ar.husqvarna.com

Armenia

Garden Land Ltd.
 61 Tigran Mets
 0005 Yerevan

Australia

Husqvarna Australia Pty. Ltd.
 Locked Bag 5
 Central Coast BC
 NSW 2252
 Phone: (+61) (0) 2 4352 7400
 customer.service@
 husqvarna.com.au

Austria / Österreich

Husqvarna Austria GmbH
 Industriezeile 36
 4010 Linz
 Tel.: (+43) 732 77 01 01-485
 service.gardena@
 husqvarnagroup.com

Azerbaijan

Firm Progress
 a. Aliyev Str. 26A
 1052 Bakı

Belgium

Husqvarna België nv/sa
 Gardena Division
 Rue Egide Van Ophem 111
 1180 Uccle / Ukkel
 Tel.: (+32) 2 720 92 12
 info@gardena.be

Bosnia / Herzegovina

SILK TRADE d.o.o.
 Industrijska zona Bukva bb
 74260 Tešanj

Brazil

Husqvarna do Brasil Ltda
 Av. Francisco Matarazzo,
 1400 – 19º andar
 São Paulo – SP
 CEP: 05001-903
 Tel: 0800-112252
 marketing.br.husqvarna@
 husqvarna.com.br

Bulgaria

AGROLAND България АД
 бул. 8 Декември, №13
 Офис 5
 1700 Студентски град
 София
 Тел.: (+359) 246669 10
 info@agroland.eu

Canada / USA

GARDENA Canada Ltd.
 100 Summerlea Road
 Brampton, Ontario L6T 4X3
 Phone: (+1) 905 792 9330
 info@gardenacanada.com

Chile

Maquinarias Agroforestales
 Ltda. (Maga Ltda.)
 Santiago, Chile
 Avda. Chesterton
 # 8355 comuna Las Condes
 Phone: (+56) 2 202 4417
 Zipcode: @maga.cl
 Dátone: 7560330

China

Husqvarna (Shanghai)
 Management Co., Ltd.
 富世华 (上海) 管理有限公司
 3F, Benq Square B,
 No207, Song Hong Rd.,
 Chang Ning District,
 Shanghai, PRC. 200335
 上海市长宁区淞虹路207号明
 基广场B座3楼, 邮编: 200335

Colombia

Husqvarna Colombia S.A.
 Calle 18 No. 68 D-31, zona
 Industrial de Montevideo
 Bogotà, Cundinamarca
 Tel. 571 2922700 ext. 105
 jairo.salazar@
 husqvarna.com.co

Costa Rica

Compania Exim
 Euroberoamericana S.A.
 Los Colegios, Moravia,
 200 metros al Sur del Colegio
 Saint Francis – San José
 Phone: (+506) 297 6883
 exim_euro@racsa.co.cr

Croatia

Husqvarna Austria GmbH
 Industriezeile 36
 4010 Linz
 Tel.: (+43) 732 77 01 01-485
 service.gardena@
 husqvarnagroup.com

Cyprus

Med Marketing
 17 Digeni Akrita Ave
 P.O. Box 27017
 1641 Nicosia

Czech Republic

Husqvarna Česko s.r.o.
 Türkova 2319/5b
 149 00 Praha 4 – Chodov
 Bezpłatná infolinka:
 800 100 425
 servis@cz.husqvarna.com

Denmark

GARDENA DANMARK
 Løjrvæg 19, st.
 3500 Værløse
 Tlf.: (+45) 70 26 4770
 husqvarna@husqvarna.dk
 www.gardena.com/dk

Dominican Republic

BOSQUESA, S.R.L
 Carretera Santiago Licey
 Km. 5 ½
 Esquina Copal II,
 Santiago
 Dominican Republic
 Phone: (+809) 736-0333
 josebrosquesa@claro.net.do

Ecuador

Husqvarna Ecuador S.A.
 Агрос Е1-181 y 10 de
 Agosto Quito, Pichincha
 Tel. (+593) 22800739
 francisco.jacom@
 husqvarna.com.ec

Estonia

Husqvarna Eesti OÜ
 Valdeku 132
 EE-11216 Tallinn
 info@gardena.ee

Finland

Oy Husqvarna Ab
 Gardena Division
 Lautatarhankatu 8 B / PL 3
 00581 HELSINKI
 www.gardena.fi

France

Husqvarna France
 9/11 Allée des pierres mayettes
 92635 Gennevilliers Cedex
 France
 http://www.gardena.com/fr
 N° AZUR: 0 810 00 78 23
 (Prix d'un appel local)

Georgia

Transporter LLC
 8/57 Bellashvili street
 0159 Tbilisi, Georgia
 Phone: (+995) 322 14 71 71

Great Britain

Husqvarna UK Ltd
 Preston Road
 Aycliffe Industrial Park
 Newton Aycliffe
 County Durham
 DL5 6UP
 info.gardena@
 husqvarna.co.uk

Greece

Π. ΠΑΠΑΔΟΠΟΥΛΟΣ ΑΕΒΕ
 Λεωφ. Αθηνών 92
 Αθήνα
 Τ.Κ. 104 42
 Ελλάδα
 Τηλ. (+30) 210 51 93 100
 info@papaopoulos.com.gr

Hungary

Husqvarna Magyarorszáig Kft.
 Ezred u. 1-3
 1044 Budapest
 Telefon: (+36) 1 251-4161
 vezoszolgalat.husqvarna@
 husqvarna.hu

Iceland

O. Johnson & Kaaber
 Tunguhalts 1
 110 Reykjavik
 oo@ojk.is

India

Husqvarna UK Ltd
 Preston Road
 Aycliffe Industrial Park
 Newton Aycliffe
 County Durham
 DL5 6UP
 info.gardena@
 husqvarna.co.uk

Italy

Husqvarna Italia S.p.A.
 Via Santa Vecchia 15
 23868 VALMADRERA (LC)
 Phone: (+39) 0341.203.111
 assistenza.italia@
 it.husqvarna.com

Japan

KAKUICHI Co. Ltd.
 Sumitomo Realty &
 Development Kojimachi
 BLDG., 8F
 5-1 Nibanencho
 Chiyoda-ku
 Tokyo 102-0084
 Phone: (+81) 33 264 4721
 m_ishihara@kaku-ichi.co.jp

Kazakhstan

LAMED Ltd.
 155/1, Tazhibayev Str.
 050060 Almaty
 IP Schmidt
 Abayavenue 3B
 110 005 Kostanay

Korea

Kyung Jin Trading Co., LTD.
 108-4, SunDuk Bld.,
 YangJae-dong,
 Seocho-gu,
 Seoul, (zipcode: 137-891)
 Phone: (+82) (0)2 574-6300

Kyrgyzstan

Alye Maki
 av. Moladaya Guardir J 3
 720014
 Bishkek

Lithuania

Husqvarna Latvija SIA
 Ulbrokas 19A
 LV-1021 Riga
 info@gardena.lv

Lithuania

UAB Husqvarna Lietuva
 Ateities pl. 77C
 LT-52104 Kaunas
 info@gardena.lt

Luxembourg

Magasins Jules Neuberg
 39, rue Jacques Stas
 Luxembourg-Gasperich 2549
 Case Postale No. 12
 Luxembourg 2010
 Phone: (+352) 40 14 01 01
 ap@neuberg.lu

Mexico

AFOSA
 Av. Lopez Mateos Sur # 5019
 Col. La Calma 45070
 Zapopan, Jalisco
 Mexico
 Phone: (+52) 33 3818-3434
 icornejo@afosa.com.mx

Moldova

Convel S.R.L.
 290A Munciei Str.
 2002 Chisinau

Netherlands

Husqvarna Nederland B.V.
GARDENA Division
 Postbus 50131
 1305 AC ALMERE
 Phone: (+31) 36 521 00 10
 info@gardena.nl

Neth. Antilles

Jonka Enterprises N.V.
 St. Rosa Weg 196
 P.O. Box 8200
 Curaçao
 Phone: (+599) 9 767 66 55
 pgm@jonka.com

New Zealand

Husqvarna New Zealand Ltd.
 PO Box 76-437
 Manukau City 2241
 Phone: (+64) (0) 9 9202410
 support.nz@husqvarna.co.nz

Norway

Husqvarna Norge AS
 Gardena Division
 Trøskneveien 36
 1708 Sarpsborg
 info@gardena.no

Peru

Husqvarna Perú S.A.
 Jr. Ramón Cárcamo 710
 Lima 1
 Tel.: (+51) 1 3320 400 ext. 416
 juan.remuzgo@
 husqvarna.com

Poland

Husqvarna
 Poland Spółka z o.o.
 ul. Wysockiego 15 b
 03-371 Warszawa
 Phone: (+48) 22 330 96 00
 gardena@husqvarna.com.pl

Portugal

Husqvarna Portugal, SA
 Lagoa - Albarraque
 2635 - 595 Rio de Mouro
 Lda.
 Tel.: (+351) 21 922 85 30
 Fax: (+351) 21 922 85 36
 info@gardena.pt

Romania

Madex International Srl
 Soseaua Odail 117-123,
 RO 013603 Bucuresti, S.1
 Phone: (+40) 21 352.76.03
 madex@mes.ro

Russia / Россия

ООО „Хускварна“
 114100, Московская обл.,
 г. Химки,
 улица Ленинградская,
 владение 39, стр.6
 Бизнес Центр
 „Химки Бизнес Парк“,
 помещение ОВ02_04
 http://www.gardena.ru

Serbia

Domel d.o.o.
 Autoput za Novi Sad bb
 11279 Belgrade
 Phone: (+381) 11 848 88 12
 miroslav.jejina@domel.rs

Singapore

Hy-Ray PRIVATE LIMITED
 40 Jalan Pemimpin
 #02-08 Tat Ann Building
 Singapore 577185
 Phone: (+65) 6253 2277
 shiying@hyray.com.sg

Slovak Republic

Husqvarna Česko s.r.o.
 Türkova 2319/5b
 149 00 Praha 4 – Chodov
 Bezpłatná infolinka:
 800 154 044
 servis@sk.husqvarna.com

Slovenia

Husqvarna Austria GmbH
 Industriezeile 36
 4010 Linz
 Tel.: (+43) 732 77 01 01-485
 service.gardena@
 husqvarnagroup.com

South Africa

Husqvarna
 South Africa (Pty) Ltd
 Postnet Suite 250
 Private Bag X6,
 Cascades, 3202
 South Africa
 Phone: (+27) 33 846 9700
 info@gardena.co.za

Spain

Husqvarna España S.A.
 Calle de Rivas nº10
 28052 Madrid
 Phone: (+34) 91 708 05 00
 atencioncliente@gardena.es

Suriname

Agrofix n.v.
 Verlengde Hogestraat #22
 Phone: (+597) 472426
 agrofix@sr.net
 Pobox: 2006
 Paramaribo
 Suriname – South America

Sweden

Husqvarna AB
 Gardena Division
 S-561 82 Huskvarna
 gardenaorder@husqvarna.se

Switzerland / Schweiz

Husqvarna Schweiz AG
 Consumer Products
 Industriestrasse 10
 5506 Mägenwil
 Phone: (+41) (0) 62 887 37 90
 info@gardena.ch

Turkey

Dost Bağçe Diş Ticaret
 Müessesli A.Ş.
 Yunus Mah. Adil Sok. No:3
 İc Kapı No: 1 Kartal
 34873 İstanbul
 Phone: (+90) 216 38 93 939
 info@dstbahce.com.tr

Ukraine / Україна

ТОВ „Хускварна Україна“
 вул. Васильківська, 34,
 офіс 204-р
 03022, м. Київ
 Тел. (+38) 044 998 90 02
 info@gardena.ua

Uruguay

FELI SA
 Entre Rios 1083 CP 11800
 Montevideo – Uruguay
 Tel: (+598) 22 03 18 44
 info@felisa.com.uy

Venezuela

Corporación Casa y Jardín C.A.
 Av. Caroni, Edif. Trezmen, PB.
 Colinas de Bello Monte.
 1050 Caracas.
 Tlf: (+58) 212 992 33 22
 info@casayjardin.net.ve

19005-20.963.01/0819
 © GARDENA
 Manufacturing GmbH
 D-89070 Ulm
 http://www.gardena.com